

(19)



Europäisches Patentamt
European Patent Office
Office européen des brevets

(11) Publication number:

0 395 424
A2

(12)

EUROPEAN PATENT APPLICATION

(21) Application number: 90304568.0

(51) Int. Cl.⁵: H03H 17/06

(22) Date of filing: 26.04.90

(30) Priority: 26.04.89 US 344190


(43) Date of publication of application:
31.10.90 Bulletin 90/44(94) Designated Contracting States:
DE FR GB(71) Applicant: Hewlett-Packard Company
Mail Stop 20 B-O, 3000 Hanover Street
Palo Alto, California 94304(US)(72) Inventor: Adcock, James L.
2152 N. 112th Street, No. 101
Seattle, Washington 98133(US)(74) Representative: Colgan, Stephen James et al
CARPMAELS & RANSFORD 43 Bloomsbury
Square
London WC1A 2RA(GB)

(54) Filter and method for whitening digitally generated noise.

(57) A digital filter (10) for prewhitening digital noise is realized without the need to perform multiplication or division operations to weight any of the digital samples. Instead, the data samples that need weighting are bit shifted to achieve multiplication or division by a power of two. In the preferred embodi-

ment, the filtering function is $1-z^{-8}$, where z is a single sample delay. This function is implemented by bit shifting one sample three bits to the right and computing the difference between it and an adjacent sample.

FIG. 1



EP 0 395 424 A2

FILTER AND METHOD FOR WHITENING DIGITALLY GENERATED NOISE

Field of the Invention

The present invention relates to digital noise sources, and more particularly relates to a method and apparatus for whitening the noise generated by such sources.

Background and Summary of the Invention

Random noise is used advantageously in a variety of applications, such as in exciting electrical or mechanical systems under test. In such applications, the system's response to the noise stimulus can be analyzed to predict the system's response to a multitude of other conditions for which individual testing is impractical.

Important in such analyses is the requirement that the spectral distribution of energy in the noise signal be constant throughout the frequency range of interest. If it is not, then subsequent analysis cannot determine whether a system's particularly strong response at one noise frequency was due to a resonance at that frequency or whether the noise signal simply had a local maximum at that frequency component, prompting an exaggerated response. While a noise signal with a uniform spectral power distribution may be simple to conceptualize, it is often not simple to realize.

A common technique for generating relative low frequency noise (as opposed to microwave noise and the like) is to periodically produce a digital random number and convert it into analog form using a digital-to-analog converter (DAC). The analog signal output by the DAC changes at periodic intervals as new random numbers are provided to it, resulting in a time varying "noise" signal. This approach is termed the uniformly distributed digital random number technique.

The periodic operation of this random number generator affects the frequency spectrum of the resulting noise signal. For example, if a new random number is provided to the DAC every four microseconds, the resulting noise signal will have a nominal bandwidth of (1/4 microseconds), or 250 kilohertz. Above 250 kilohertz, the power output by the DAC begins to rolloff more and more. Even below 250 kilohertz, the noise is not perfectly flat but begins to diminish with frequency. These irregularities are due to a phenomenon commonly known as $\sin(x)/x$ rolloff, which is present because the random numbers are produced periodically and the analog samples corresponding thereto are held

constant for the periodic interval. ($\sin(x)/x$ is the Fourier transform of a constant signal of finite duration.) Elimination of this phenomenon would require that ideal impulses of voltage be output by the DAC, a feat that cannot be realized in practice.

$\sin(x)/x$ rolloff is not entirely disadvantageous. It tends to limit the power of the noise to a certain bandwidth that can be controlled by setting the "sampling frequency" -- the update rate of the DAC. However, at the corner frequency of the $\sin(x)/x$ rolloff (250 kilohertz in the above example), the response of the noise is already several dB down. Ideally, this non-flatness in-band would be limited to less than a dB.

This rolloff problem can be overcome by filtering the noise signal with a filter whose passband characteristics compensates for the $\sin(x)/x$ droop, resulting in an approximately flat response over the frequency band of interest. Such filters are termed "prewhitening" filters and are typically implemented in digital form for use in the digital portion of the noise generator.

As is known in the art, digital filters operate by summing a weighted series of data samples. The weighting coefficients are selected to achieve a desired passband characteristic. Unfortunately, digital filters are usually complex and expensive. For example, such a filter must usually perform several multiplication or division operations per cycle to weight the samples in their proper relationship. These operations are computationally intensive and time consuming. Due to the poor performance of conventional microprocessors at these tasks, specialized hardware that has been optimized to execute the filtering operations is usually required. Such specialized hardware is economically impractical to use in many applications, such as in simple noise sources.

The present invention provides the advantages of digital filtering without the usual high cost and complexity. This is accomplished by selecting a filter characteristic that can be implemented without performing any multiplication or division operations.

In particular, the present invention implements a filtering function expressed as $1 - z^{-8}$, where z represents a single sample delay. The weighting coefficients are thus 1 and 1/8. The "1" coefficient requires no multiplication. Multiplication by the "1/8" coefficient is effected by simply bit shifting the data sample three bits to the right. The subtraction operation is conventional and can be easily effected by a simple CPU. The result is a fast and simple prewhitening filter that can be easily implemented without any custom hardware.

The foregoing and additional features and ad-

vantages of the present invention will be more readily apparent from the following detailed description thereof, which proceeds with reference to the accompanying drawings.

Brief Description of the Drawings

Fig. 1 shows a representative prior art noise waveform generated using a uniformly distributed digital random number approach.

Fig. 2 shows the spectral distribution of the Fig. 1 waveform.

Fig. 3 shows the passband response of a prewhitening filter according to one embodiment of the present invention.

Fig. 4 shows a prewhitening filter according to one embodiment of the present invention represented in conventional digital filter topology.

Fig. 5 shows an apparatus for producing prewhitened noise according to the present invention.

Fig. 6 shows a flowchart of a filter process according to one embodiment of the present invention.

Fig. 7 shows the spectral distribution of a noise source that has been prewhitened using a filter according to one embodiment of the present invention.

Detailed Description

Fig. 1 shows a representative prior art noise waveform. As noted, such waveforms are conventionally generated by periodically computing a digital random number and converting the number to analog form using a digital-to-analog converter. The spectral distribution of such a waveform is shown in Fig. 2, which clearly illustrates the $\sin(x)/x$ function.

As discussed earlier, some prior art techniques have sought to mitigate the $\sin(x)/x$ effect by processing the digital samples through complex prewhitening filters. Other applications use the rippled noise signal to stimulate the system under test, but only analyze the system's response over the range across which the noise spectrum is relatively flat (i.e. the range bracketed and labelled "A" in Fig. 2).

An ideal filter for compensating the $\sin(x)/x$ noise distribution would exhibit a passband characteristic of $x \cdot \sin(x)$ and would extend the usable noise bandwidth of the source up to the first null in the noise spectrum. However, this passband cannot be realized simply. The present invention uses instead a passband function that can be realized

simply and yet offers first order compensation for the $\sin(x)/x$ noise function. This function is $F_N = R_N - R_{N-1}/8$, where F_N is the filtered noise sample, and R_N and R_{N-1} are sequential random noise samples.

The passband of this function can be determined by decomposing the function into its component parts. The passband of the origin impulse R_N is 1 over all frequencies. The passband of the $(-1/8)$ impulse at $T=1$ is $-\cos \omega/8$, which rises from $-1/8$ to $1/8$ over the frequency range 0 to π . The summed passband is shown in Fig. 3 in solid lines; the two decomposed passbands are shown in dashed lines. For low frequency noise (i.e. less than about $(\pi/2) \cdot 3$, it will be recognized that the gradual increase in the passband response with frequency closely counteracts the gradual decrease in the $\sin(x)/x$ function over the same range. The result is a virtually flat noise spectrum over the widened frequency range labeled 'B.'

Digital filters are conventionally implemented by cascading delay stages with output taps at the different stages. Delayed signal samples from the different taps are applied to respective weighting circuits and the weighted samples are summed to form respective filtered output samples from the filter. Fig. 4 shows the present filter function represented in this conventional filter topology. As can be seen, such an arrangement requires the use of at least one multiplier stage to accomplish the weighting by a factor of $-1/8$.

In the present invention, by contrast, this weighting operation is accomplished by bit shifting the delayed sample 3 bits to the right. Bit shifting operations are included in the instruction set of even the most rudimentary microprocessors and execute very quickly. The calculation of the difference between the delayed, bit shifted sample with the current sample is also an operation that any microprocessor can perform quickly.

An apparatus 10 for generating and filtering a noise sequence according to the present invention is shown in Fig. 5. This apparatus is described in greater detail in copending U.S. application Serial No. 345264 entitled SIGNAL GENERATOR METHOD AND APPARATUS, the disclosure of which is incorporated herein by reference European Application No. . Although not necessary to the present invention, illustrated apparatus 10 includes a digital mixer for translating the noise spectrum up from baseband to a desired frequency of interest.

Apparatus 10 comprises a control microprocessor 12 with associated memory and I/O, a pattern memory 14, a pattern memory controller 16, a digital local oscillator 18, a digital multiplier 20 and a digital-to-analog converter 22. These elements are interconnected by data buses 24 and control lines 26.

The control microprocessor 12 in the illustrated

embodiment is a Motorola 68000 series CPU that controls most of the functions of a host instrument in which the noise source 10 is embodied. Associated with CPU 12 is a memory 28 in which I/O and instrument operation routines are stored. Also included in this memory are the random number generator routine and the prewhitening filter routine. Fig. 6 is a flowchart illustrating the prewhitening filter routine. The random number generator routine is conventional and many such routines are known in the art.

Pattern memory 14 is a static RAM that can be loaded with noise samples produced by CPU 12 in accordance with the above-described process. This memory has space sufficient to store several such noise sequences or may also store other signal waveforms, such as a chirp or the like. Provision is made for storing complex pattern data, although the noise sequences generated according to the present invention are purely real.

Control microprocessor 12 can be used to control all aspects of the pattern memory's operation. However, in the preferred embodiment, additional memory controller circuitry 16 is provided to reduce the processing burden on the CPU. This controller circuitry includes several subcircuits, such as a Source Address Register, a DMA Load Counter, a RAM Run Counter, a Data Register and an End of Cycle Detector.

The Source Address Register indicates to the CPU the base address in pattern memory 14 at which to begin loading an incoming noise sequence. The DMA Load Counter indexes from this base address to indicate the successive locations in the pattern memory in which bytes of an incoming sequence are to be stored. The Memory Run Counter performs the analogous function during the reading of the sequence from the pattern memory, indexing successive memory locations from which sequence samples are to be read. The Data Register holds incoming pattern data that is to be loaded into the pattern RAM until the RAM is ready to allow the transfer. This register permits the RAM to output a sequence without delaying the CPU if the CPU simultaneously needs to download a new sequence into the RAM. Finally, the End of Cycle Detector selects the length of the sequence that is to be read from the pattern memory. In the illustrated embodiment, the noise sequence stored in RAM can be from 256 to 32768 points long, in powers of two. When the End of Cycle Detector indicates that a complete sequence has been placed back, a variety of operations can be initiated. The sequence can start playing back again from the beginning, causing a repetitive noise signal to be generated. Alternatively, the waveform can be turned off, causing a "single shot" noise burst. Still further, a signal can be sent to the CPU

12 to trigger execution of another function.

Noise sequence data output from the memory 14 is provided to a digital multiplier 20 that multiplies the noise sequence with a data stream corresponding to a complex sinusoid from local oscillator 18. Local oscillator 18 is a ROM based source that operates in conjunction with CPU 12 to provide a local oscillator data stream. The mixing of these two data streams serves to translate the baseband noise sequence to a higher frequency.

The digital data stream output from the multiplier 20 is converted to analog form using a digital-to-analog converter (DAC) 22. Since the DAC holds each sample for a finite time period (corresponding to the apparatus's 262.144 Hz sampling rate), a $\sin(x) \cdot x$ term is introduced into the output signal's frequency spectrum. This ripple is removed by an analog reconstruction filter 34 dedicated to this particular function. Filter 34 also serves to suppress sidebands and harmonics of the desired output signal. The filtered analog noise signal is then output from the instrument for application to the system under test.

It will be recognized that the process of the present invention can be used on a continuous basis to filter in real time an unending stream of digital random numbers as they are produced. In one such implementation, the filtering process is embedded in the routine that generates the random numbers itself and is executed as part of the generation process. In other embodiments, a limited set of random numbers is generated and processed to effect the filtering operation. This latter process is illustrated in Fig. 6. A set of 1024 random number samples R_N is calculated and is processed to yield a corresponding set of filtered samples F_N .

Having described and illustrated the principles of my invention with reference to a preferred embodiment thereof, it will be apparent that the invention can be modified in arrangement and detail without departing from such principles. For example, while the bit shifting and subtracting operations needed to implement the preferred filtering operation are illustrated as being performed by a microprocessor, in alternative embodiments other components may be used. In one such alternative embodiment, for example, a shift register is used to perform the bit shifting operation. The subtracting operation is performed by converting the shifted sample and the unshifted sample into analog form and using an analog operational amplifier to determine the difference. The output signal is then already in analog form. Similarly, while the preferred implementation of the invention uses the filter function $1 - z^{-8}$ (where z is a single sample delay), other functions can readily be used with comparable effect. Such other functions include, by

way of example, $1/8 - z$; $1 - 8z$; $8 - 1z$; $16 - 2z$, etc. etc.

In view of the wide variety of embodiments to which the principles of my invention can be applied, it should be recognized that the illustrated embodiment is to be considered exemplary only and not as limiting the scope of my invention. Instead, I claim as my invention all such modifications as may come within the scope and spirit of the following claims and equivalents thereto.

Claims

1. A method of generating a whitened noise sequence comprising the steps:

(a) producing a first random number represented in digital form;

(b) producing a second random number represented in digital form;

(c) bit shifting at least one of said samples to weight the first and second samples in a one to eight ratio;

(d) computing a difference between the first and second random numbers after the aforesaid shifting;

(e) providing said difference as an element of the noise sequence;

(f) producing an additional random number represented in digital form; and

(g) repeating steps (c) through (f) with the second random number as the first and with the additional random number as the second.

2. The method of claim 1 in which the repeating of steps (c) through (f) is done periodically.

3. The method of claim 1 in which the bit shifting comprises shifting one of said first or second random numbers three places.

4. A filter (10) for prewhitening a sequence of noise signals, comprising:

input means (12) for receiving first and second digitized noise signals;

bit shifting means (12) coupled to said input means for bit shifting at least one of said first and second digitized noise signals to weight said signals in a one to eight ratio; and

computing means (12) coupled to the bit shifting means for computing a difference between said signals after bit shifting and for providing said difference as an element of an output, filtered noise sequence.

5. The filter of claim 4 in which the bit shifting means includes means (12) for bit shifting one of said first or second digitized noise signals three places.

6. The filter of claim 4 in which the input means, the bit shifting means and the computing means all comprise a microprocessor (12).

7. In a method of digitally filtering a sequence of digital noise samples that includes the step of summing a series of weighted data samples, an improvement for reducing the computational intensity of the filtering operation, the improvement comprising weighting at least one of said digital noise samples by bit shifting said sample to achieve multiplication or division by a power of two.

FIG. 1





FIG. 4






FIG. 6







FIG. 3









Europäisches Patentamt
European Patent Office
Office européen des brevets



Publication number:

0 395 424 A3

12

EUROPEAN PATENT APPLICATION

21 Application number: 90304568.0

51 Int. Cl.⁵: H03H 17/06

22 Date of filing: 26.04.90

30 Priority: 26.04.89 US 344190

43 Date of publication of application:
31.10.90 Bulletin 90/44

84 Designated Contracting States:
DE FR GB

88 Date of deferred publication of the search report:
12.06.91 Bulletin 91/24

71 Applicant: Hewlett-Packard Company
Mail Stop 20 B-O, 3000 Hanover Street
Palo Alto, California 94304(US)

72 Inventor: Adcock, James L.
2152 N. 112th Street, No. 101
Seattle, Washington 98133(US)


74 Representative: Colgan, Stephen James et al
CARPMAELS & RANSFORD 43 Bloomsbury
Square
London WC1A 2RA(GB)

54 Filter and method for whitening digitally generated noise.

57 A digital filter (10) for prewhitening digital noise is realized without the need to perform multiplication or division operations to weight any of the digital samples. Instead, the data samples that need weighting are bit shifted to achieve multiplication or division by a power of two. In the preferred embodi-

ment, the filtering function is $1-z/8$, where z is a single sample delay. This function is implemented by bit shifting one sample three bits to the right and computing the difference between it and an adjacent sample.

FIG. 4



EP 0 395 424 A3



European
Patent Office

EUROPEAN SEARCH REPORT

Application Number

EP 90 30 4568

DOCUMENTS CONSIDERED TO BE RELEVANT			
Category	Citation of document with indication, where appropriate, of relevant passages	Relevant to claim	CLASSIFICATION OF THE APPLICATION (Int. Cl.5)
Y	US-A-3 979 701 (TOMOZAWA) * Abstract; column 4, lines 3-21; figure 1 * - - -	1,2,4,7	H 03 H 17/06
A		3,5	
Y	IEEE TRANSACTIONS ON COMPUTERS, vol. C-20, no. 3, March 1971, pages 270-281, New York, US; A.C. DAVIES: "Properties of waveforms obtained by nonrecursive digital filtering of pseudorandom binary sequences" * Page 271, left-hand column, lines 19-32; page 273, left-hand column, lines 7-28; page 274, left-hand column, lines 5-13; figures 2,3 * - - - - -	1,2,4,7	
			TECHNICAL FIELDS SEARCHED (Int. Cl.5)
			H 03 H G 06 F
The present search report has been drawn up for all claims			
Place of search		Date of completion of search	Examiner
The Hague		21 March 91	WRIGHT J.P.
CATEGORY OF CITED DOCUMENTS X: particularly relevant if taken alone Y: particularly relevant if combined with another document of the same category A: technological background O: non-written disclosure P: intermediate document T: theory or principle underlying the invention E: earlier patent document, but published on, or after the filing date D: document cited in the application L: document cited for other reasons &: member of the same patent family, corresponding document			